46-FX-SL SERIES
SINGLEMODE

10/100Base-T to 100Base-FX Ethernet Media Converter / 3 Port Switch

FEATURES:

- Complete Fiber Optic to Twisted Pair Media Interface
- Auto MDI / MDIX Detection
- Auto Negotiate 10/100 Ports
- Link and Activity Indicators for UTP and Fiber Ports
- Singlemode and Multimode Fiber Versions Available

SPECIFICATIONS:

Ethernet:
Data Rate
Auto negotiated ..... 10/100 Mb/s
Connector.....RJ45

Optical:
One Fiber.....1310/1550 nm
Two Fiber.....1310 nm
Distance (9/125um)..... 20 km
FX 9/125u..... 20 km
Loss Budget .....20 dB
Connector..... SC, ST

Power:
Voltage ..... 12 VDC
Current.....500 mA
Connector.....2 Pin Terminal Block

Power Supply:
Module: 12VDC(AFI Part #: PS-12D+)
Rack Card: (AFI Part #: SR-20/2)

Environmental:
Temperature.....-40 °C to 75 °C
Humidity.....5 % to 95 %

Size:
Module.....…4¼" x 4¼" x 1⅛"
Rack Card One Slot ..... 6½" x 1" x 5"

3/14/11JPK

The American Fibertek 46SL Series transmits and receives (2) copper 10/100 BaseT Ethernet signals at the RJ45 ports and (1) optical 100 Base-FX over 1 or 2 singlemode fibers. The system is comprised of two units forming a point-to-point communications link.

The system is designed to be completely transparent with auto negotiation features which automatically configures the unit for the correct speed (10/100 BaseT). Auto MDI/MDIX operation eliminates the potential need for crossover cables. Diagnostic indicators provide a quick visual indication of system status.

Equipment may be ordered as stand alone modules or rack cards that are mounted in the American Fibertek Card Cage: SR-20/2

ORDERING INFORMATION:

MX-46-FX-SL-AA	Two Fiber Module FX Singlemode
RX-46-FX-SL-AA	Two Fiber Rack Card FX Singlemode
MTX-46-FX-SL-AA	One Fiber Module Transmitter FX Singlemode
MRX-46-FX-SL-AA	One Fiber Module Receiver FX Singlemode

Replace AA with ST or SC to specify the desired optical connector

american fibertek inc. 120 Belmont Drive, Somerset, NJ, USA 08873-1204
Phone: 732.302.0660 FAX: 732.302.0667 Toll Free: 877.234.7200 Email: mail@americanfibertek.com